



TRINITY PLEXI 6V6 CATHODE BIAS S.S. RECTIFIER (390 v b+, 300R, 1K5, 15K, 100K/15K PI)

	1	2	3	4	5	6	7	8	9
V1	168		1.5			127		0.8	
V2	145		0.9			239		146	
V3	188	20	32			184	32	20	
V4			373	369				25.4	JJ 6V6S
V5			370	369					100%
	A=386	B=371	C=280	D=240	E=202				

REV.	DESCRIPTION	DATE	BY	Notes
1	First Release based on M.Huss	10Aug19	SC	1. Resistors - 1 watt carbon film except as noted
2	Release updated to 18 Watt specs	24Aug19	SC	2. Input 68K & 1M are 1W Carbon Film
3	Changed PI Tail R to 15K	25Aug19	SC	3. 0.01 & 0.02 Coupling Caps Sozo or Mallory 150
4	Notes 5 & 6 added per Phil Rowley	28Aug19	SC	4. Metal oxide resistors thru power supply, plates & on the power tube screens.
5	C2 changed to .022 from .0022	27Mar21	SC	5. Bypass R9 with 0.47uF, 0.33uF or 0.22uF cap to get a more effect between Fat switch On or Off. 6. Increase C13 to 1000uF - 2000uF to tighten up the amp and give it a Fixed Bias feel. 7. Tighten up channel with .0047 for C2

THIS DESIGN PROPERTY OF TRINITY AMPS INC. FOR PERSONAL USE ONLY

Trinity Amps

Custom Plexi 6V6

SIZE	FSCM NO	DWG NO	REV
SCALE	1 : 1	SHEET	20 OF 66