



# Trinity TRIWATT 6V6 Voltage Chart

AC Mains Voltage 122VAC;B+ 460 VDC no tubes installed;442 VDC with tubes

6V6 Bias	15 ma min	23 ma max
KT-66 bias	30 ma min	40 ma max

 <p><b>12AX7/12AT7</b></p>		 <p><b>6V6</b></p>							
TUBE	Pin 1	Pin 2	Pin 3	Pin 4	Pin 5	Pin 6	Pin 7	Pin 8	Pin 9
<b>V1</b> (12AX7/ECC83)	150	0	1.2	--	--	120	0	1.0	--
<b>V2</b> (12AX7/ECC83)	179	0	1.2	--	--	106	0	0.7	--
<b>V3</b> (12AX7/ECC83)	269	67	71	--	--	188	0	1.5	--
<b>V4 (PI)</b> (12AT7/ECC)	274	71	74	--	--	236	64.4	74	
<b>V5 6V6 (1)</b>	0	--	441	411	-39 *	-39 *	--	0.02	
<b>V6 6V6 (2)</b>	0	--	441	411	-39 *	-39 *	--	0.02	